

Switch mode with transformer power supplies series (Grade 1, 2)

Features:

- **compliance with standards**
 - **alarm system EN50131-6 for grades 1, 2 (Grade 1, 2);**
 - **access control EN60839-11 for grades 1, 2 (Grade 1, 2);**
- switch mode with transformer power supply;
- automatic, cyclic battery test;
- protection against deep discharge of battery;
- technical outputs OC
 - EPS – technical output indicating AC power loss;
 - APS – technical output of battery failure;
 - option to switch to relay outputs (AWZ639 relay module);
- „START” button - safe, manual connection of power supply from battery without the presence of AC 230V voltage;
- possibility of selecting battery charging current;
- warranty: 5 years from the production date.



Code	Output voltage	Output current	Battery charging current	Space for battery	Dimensions W×H×D+D ₁
AWZG2-12V2A-B	13,8VDC	2A	0,2A / 0,5A	7Ah	205×237×82+8
AWZG2-12V3A-C		3A	0,5A / 1A	17Ah	235×305×82+8
AWZG2-12V5A-C		5A	0,5A / 1A / 2A	17Ah	305×305×105+8
AWZG2-12V5A-D		5A	0,5A / 1A / 2A	40Ah	335×385×173+14
AWZG2-24V2A-B	27,6VDC	2A	0,5A / 1A	2× 7Ah	205×305×82+8
AWZG2-24V3A-C		3A	0,5A / 1A	2× 17Ah	335×385×173+14

ACCESSORIES: AWZ639



Relay module of technical outputs (conversion of OC type outputs into relay outputs).

BATTERIES

- STB
- SCB
- HPB

